

IPK - CALL FORWARD BUSY/NO ANSWER (B/NA)

Set

1. Press the **Speaker** key.
2. Dial Call Forward B/NA set code **43**.
3. Dial the destination station number or voice mail or trunk access code and the outside number.
4. Press the **Speaker** key again.

Note: Destination number for voice mail is in most cases **300**.